

SMALL AND SIMPLE...


- 1100W continuous / 2200W peak power
- LCD display - Volt/Watt/Battery Level
- Ultra silent (thermal fan)
- 2 x standard North American AC outlets
- 2 x USB charging ports 2.1A (shared)
- Tablet charging compatible from USB ports
- 3 Ft. battery cables included
- ON / OFF Remote Control (optional)

WORKS WITH...

- Hand Held Power Tools
- Televisions
- Gaming Consoles
- Home Electronics
- Small Appliances
- and more...

EN1100

1100W Power Inverter - Get power on the GO!
This heavy duty Power Inverter connects directly to a 12 Volt DC battery to power hand held power tools, televisions, gaming consoles, home electronics and small appliances in your vehicle. This unit also features an LCD display, which shows the output wattage or input voltage and battery level. With this inverter, you will never be left without power when you need it!



Product Detail:

Designation: 1100 Watt POWER INVERTER

Model: EN1100

Color: Black

AC output voltage: 120VAC/60Hz

Continuous AC output power: 1100W

Peak output power: 2200W

AC output wave form: Modified sine wave

AC output frequency: 60 ± 3Hz

2 x USB DC output current: 2.1 Amp (Shared)

Typical Weight (lbs): 3.16 lbs

Dimensions (in): 2.72(H) x 10.98(L) x 5.59(W)

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication
Contents herein do not constitute a warranty
©Energizer / All Rights Reserved

Before Using Your Power Inverter:
Please read all instructions and cautionary markings on the package and manual

Power Bright Technologies
2825 N. University Drive, Suite 210
Coral Springs, FL 33065
T: 866-295-6775
www.EnergizerPower.com